

Bibich Digital Presenter Wiring

Required: VGA splitter

1. Plug one VGA cable from the back of the computer to the VGA In or “PC” port
2. Plug another VGA from the VGA Out or “Monitor” port to the back of the monitor
3. The next cable goes from the VGA Out or “Monitor” port to the VGA In port on the Digital Presenter
4. The final cable goes from the VGA out port on the Digital Presenter, to the wall or projector
5. Then the teacher can use the “Int / Ext” button on the digital presenter to choose whether the Digital Presenter or the computer is shown
6. If it was done correctly the computer monitor will continue to display, while the projector image can be switched from computer to digital presenter

